## **SELECTION OF TYPE OF BEARING REQUIRED**

Table 20.1 Guide for general application

	Bearing bore	Sealed (Se) or shielded (S)	Load capacity		Allowable	Coefficient	
Design of bearing			Radial	Axial	misalignment (degrees) <sup>(4)</sup>	of Friction <sup>(5)</sup>	Bearing section
Single row deep groove ball	Cylindrical	1 or 2 Se 1 or 2 S	Light and medium	Light and medium	0.01 to 0.05	0.0015	
Self-aligning double row ball	Cylindrical or tapered	2 S	Light and medium	Light	2 to 3	0.0010	<b>E</b>
Angular contact single row ball	Cylindrical		Medium (1)	Medium and heavy		0.0020	
Angular contact double row ball	Cylindrical		Medium	Medium		0.0024	
Duplex	Cylindrical		Light <sup>(2)</sup>	Medium		0.0022	
Cylindrical roller single row	Cylindrical		Heavy	(3)	0.03 to 0.10	0.0011	
Cylindrical roller, double row	Cylindrical		Heavy			0.0011	
Needle roller single row	Cylindrical		Heavy			0.0025	
Tapered roller single row	Cylindrical		Heavy (1)	Medium and heavy		0.0018	
Spherical roller double row	or tapered		Very heavy	Light and medium	1.5 to 3.0	0.0018	
Thrust ball single row	Cylindrical			Light and medium		0.0013	
Angular contact thrust ball double row	Cylindrical			Medium		0.0013	P
Spherical roller thrust	Cylindrical		Not exceed 55% of simultane- ously acting axial load	Heavy	1.5 to 3.0	Refer to manu- facturer	<b>⊒</b>

Information given in this chart is for general guidance only.

- Must have simultaneously acting axial load or be mounted against opposed bearing.
- Must carry predominant axial load.
- Cylindrical roller bearings with flanges on inner and outer rings can carry axial loads providing the lubrication is adequate.
- (4) The degree of misalignment permitted is dependent on internal design and manufacturers should be consulted.
- The friction coefficients given in this table are approximate and will enable estimates to be made of friction torque in different types of bearings.

Friction torque =  $\mu$  P d/2. × 10<sup>-3</sup> Nm

Where P = bearing load, N d = bearing bore diameter, mm

 $\mu$  = friction coefficient.